INFINITY-RENT G26KS-M

50Hz@1500RPM 400/230V 3PH









Picture for illustration purposes only

Overall performance	G26KS-M
PRP Continuous power kVA	25.0
PRP Continuous power kW	20.0
LTP Stand-by power kVA	27.5
LTP stand-by power kW	22.0
Power factor cos fiq	0.8
Voltage VAC	400/230
Frequency Hz	50
Ampere PRP/LTP	36 / 40
Speed RPM	1500

Dimensions and noise level

Length mm	1802
Width mm	752
Height mm	1130
Net Weight kg	677
Gross Weight kg	-
Sound pressure at 7 mt dBA	72.00

General features

Silent Generator specifically designed for mobile application and Rental. Easy to use and handle.

Mounting last generation of engine with low emission, for a clean power.

Frame:

- Heavy duty fabricated welded base plate with high quality steel UNI S235 JR
- Heavy duty rubber anti-vibration mountings
- Fuel tank with drain plug and retention basin
 Base with bilateral forklift pockets allow lifting from all sides

- No.4 Large doors for easy access for service and maintenance Electro-galvanized sheet DC01+ZE25/25 (EN 10152: 2009)
- High precision sheet cutting with nitrogen laser technology to avoid oxidation
- Sandblasting and cataphoresis treatment of intake / exhaust grids
- Weatherproof sealed joints
- Lockable handles in each door
 Grey RAL 7035 "orange peel" specific powder coat paint for outdoor usage
- Coolant refilling specific hatch
- Fuel filler outside enclosure
- Central lifting hook Ecological Sound foam: 100% Recyclable, fire-proof self-extinguishing class1 fire-reaction compliant washable, mechanically fixed to the frame

- Supersilent, Residential type, integrated in the canopy
- With aluminum coating

Control Panel:

- Metal Control panel with protective back cover
- Dedicated area to make easier the electrical connection to the load

All units and components are prototype tested, factory build and production tested. A specific control procedure during the several stages of production ensures long life and reliability.

Data reference

Standard reference conditions temperature 25°C, altitude 1-1000m asl, relative humidity 30%, atmospheric pressure 100 kPa (1 bar), power factor 0.8 lag, balanced load - non distortional. Fuel consumption is nominal and refers to specific weight 0.850 gr/lt. Power performance data as quoted can be obtained after the initial running-in period of the engine, during which one has to follow the instructions of the engine manufacturer as stated in the use and maintenance manual of the specific engine. The tolerance shown by the engine manufacturer is +/- 5%. Sound power values refer to free field conditions: the installation site may influence the values. Dimensions, weights and other specifications contained in the technical data sheet and related attachments are nominal, subject to tolerances and refer to the model with standard equipment; any optional and additional Dimensions, weights and other specifications contained in the technical data sheet and related attachments are nonlinial, subject to tolerances and refer to the model with standard equipment; any optional and additional equipment/accessories can modify weight, dimensions, performance.P.R.P. Prime Power-Continuous power at variable load: The power that a genset can supply in continuous service at a variable load for an unlimited number of hours per year while respecting the maintenance intervals established in the environmental conditions stated by the Manufacturer, according to ISO8528-1. The average power supplied over time and any applicable overload must be less than the percentages stated by the Manufacturer.L.T.P. Limited-time running power-Limited power: The maximum power that a genset can supply for a limited time respecting the maintenance intervals established in the environmental conditions stated by the Manufacturer according to ISO 8528-1. The number of hours per year is stated by the Manufacturer. Overload is not permitted.*For reasons of transport and/or storage, liquids (oil and antifreeze) and batteries might not be included in the delivery





INFINITY-RENT G26KS-M

50Hz@1500RPM 400/230V 3PH



Engine general data

Engine brand	Kohler
Model	KDI2504M
PRP Power kW	23.10
LTP Power kW	25.40
Fuel	Diesel
Nr. cylinders	4
Air intake	Aspirated
Cooling	Water
Cubic capacity I.	2.48
Speed regulation	Mechanical
Performance Class - steady state regulator accuracy +/- %	G2 - 0.50
Load Step G1 - KWe	-
Load Step G2 - KWe	-
Load Step G3 - KWe	-
Voltage VDC	12
Emissions	Euro Stage 3A

Alternator general data

Alternator brand	Mecc-Alte
Model	ECP28-L/4C
Type of excitation	Self-excited
Type of regulation	AVR
Regulator precision +/-%	1.00
Ctrustura data	

Stru	ıctu	re o	ata

Structure data		
Type of structure	20	INFINITY-RENT
Tank capacity I.		50
Retention basin		yes
Exhaust diameter mm		50

Fuel consumption

Consumption 25% I./h	2.00
Consumption 50% I./h	3.10
Consumption 75% I./h	4.70
Consumption 100% I./h	6.30
Autonomy at 75% of load h.	≈ 11 h

Engine liquids and equipment

Type of lubricant	Oil SAE 5W40 CH-4
Lubrication capacity I.*	11.50
Type of coolant	Antifreeze liquid
Coolant capacity I.*	7.60
Air intake filter	Paper cartridge
Battery capacity Ah	50
Number of batteries*	1

Fuel system and energy balance

AC pump suction head kPa	1
Combustion air flow volume LTP m3/min	1.50
Cooling air capacity LTP m3/min	35.00
Exhaust gas flow-density LTP m3/min	4.80
Exhaust gas temperature LTP °C	510.00
Brake mean effective pressure kPa	6.50
Energy to exhaust LTP kWt	17.00
Energy to coolant LTP kWt	19.50
Energy to radiation LTP kWt	4.70

Control panel features

QFIP-4510-PT2-RENT

No. 1 CEE 32A 400V No. 1 CEE 16A 400V No. 2 CEE 16A 230V No. 1 Schuko 16A 230V Thermal breaker

Circuit breaker Controller DSE4510

Voltmeter, Frequencymeter, Ammeter
 Generator power (kW, kV Ar, kV A & pf) monitoring
 Hour meter

- Fuel level meter

- Overload (kW & kV Ar) protection

- Low oil pressure protection

- High coolant temperature protection

- Low fuel level protection

- Battery charger alternator fault

- Rpm protection

- Oil pressure and engine temperature reading Analogic fuel level instrument

Emergency stop button
Quick connector for remote start/ATS

On/off switch



Dealer



