



Generators  
PETROL GENERATORS

## Petrol Generator GSEm 3002 SB

GSEm 3002 is Petrol Generator, with output max power of 3.0kW, 230V, light and portable generator, easy to start, durable with 10 hours working time.

### Advantages:

- EURO 5 engine
- Heavy-duty, strong frame
- Manual start
- AVR System
- Big fuel tank
- Control panel with two 230V/16A AC sockets
- 12 V/DC output
- Circuit breaker Control

### Technical data:

Max Power	3000 W
Rate Power	2800 W
Dual Power	No
Voltage	230 V
Socket	2x230Vx16A
ATS Connector	No
Voltmeter	Digital display
Over Voltage Protector	Yes
Displacement	208 cc
Start System	Manual
Fuel Capacity	15 l
Run time 75% load	10 hr
LPG	No
Dimensions (LxWxH)	605x445x450 mm
Weight	45 kg

